

REMARKS

1. Claims 1-16 are pending in the present application. In this Amendment, Figs. 2 and 6, claims 1-16, the title, the abstract, and the specification have been amended. A proposed drawing amendment is enclosed.

A marked-up version of the rewritten claims, specification and abstract are attached hereto.

2. The objection to the drawings has been overcome by substituting a new reference number 25 for reference number range 1-10 in amended Figs. 1 and 6, enclosed. The specification has been amended to include the reference number 25. No new matter has been added.

3. The Examiner's objection to the specification has been overcome by deleting the term "-like" from the specification, removing references to claims, and removing reference number ranges. The specification has also been amended where appropriate to more clearly separate objects, methods and materials from specific examples. No new matter has been added.

5. The objections under 35 U.S.C. § 112, second paragraph, have been overcome by amending claims 1-16 and removing reference numbers. Claims 1, 10 and 11 have also been amended to render the claims more definite.

6. The Examiner has rejected claims 1-6 and 10-12 under 35 U.S.C. § 102(b) over U.S. Patent No. 6,172,645 to Hollander et al. ("Hollander"). A reference must disclose all elements of a claim in order to anticipate the claim under 35 U.S.C. § 102. Hollander does not disclose an expansion card provided with an antenna structure which is a rod structure, as recited in

amended claims 1, 10 and 11 of the present application. In contrast, Hollander discloses a patch antenna which may be square up to the maximum width of a standard PCMCIA card. (See Figs. 2-14 and Col. 7, lines 34-39 of Hollander).

Furthermore, the rod structure, as recited in claims 1, 10, and 11 of the present application, leaves as much space as possible for the circuit board of the card and the components placed thereon in the longitudinal direction and in the thickness direction of the card. (See Figs. 2-7 and p. 5, lines 4-7 of the present application). In contrast, Hollander discloses an antenna structure which takes up space across the much of the width and thickness of the card. (See Figs. 2-14 and Col. 7, lines 34-39 of Hollander). Therefore, since all elements of claims 1, 10 and 11 are not disclosed by Hollander, claims 1, 10 and 11 should be allowed.

Hollander also does not disclose an antenna structure arranged to be locked at its first position by first inserting it by pushing it inwards, further than its first position, wherein locking is activated, and then releasing it, and allowing it to ~~move back to its first position, as recited in claim 6 of the~~ present application. Instead, Hollander discloses only that a retraction lock device may be chosen from those well known to those of ordinary skill in the art, with a first retraction connector attached to the slide portion of the antenna and a second retraction connector attached to and disposed within the cavity. Hollander does not provide any detail about a locking mechanism, or how to activate the locking mechanism. Since all elements of claim 6 are not disclosed by Hollander, claim 6 should be allowed.

As claims 1 and 11 are allowable, and claims 2-6 and 12 depend, directly or indirectly, from claims 1 and 11, claims 2-6 and 12 are also allowable.

7. The Examiner has rejected claims 7-9 and 13-16 under 35 U.S.C. § 103(a) over Hollander in view of U.S. Patent No. 5,913,174 to Casarez et al. ("Casarez"). The Applicants respectfully note that Hollander and Casarez have been combined improperly. There is no motivation to combine Hollander and Casarez since the proposed modification would render Hollander unsatisfactory for its intended purpose of an integrated, extendible antenna which does not require the antenna to be exposed from the host computer when not in use.

Hollander discloses a locking mechanism disposed within the antenna cavity of the modem card at the end away from the antenna cavity opening for retaining the antenna within the modem card. Casarez discloses a latch mechanism having a pivoting lever and receiving slots in a card for attaching an external antenna to a modem card. Casarez further discloses the pivoting lever sliding into the receiving slots on the card for ~~locking the external antenna to the card, and removing the~~ external antenna from the card by pushing on release levers attached to the pivoting lever. The release levers extend through openings in the card to outside the card. The release levers must be accessible from a position external to the card and to the antenna to be able to push the release levers.

In order to combine the locking mechanism disclosed in Casarez with the movable antenna disclosed in Hollander, a release lever would have to be attached to the locking mechanism of Hollander disposed within the antenna cavity of the modem card at the end away from the antenna cavity opening. In order to access the

release levers, an opening would have to be made in the modem card, and in the device in which the card is placed. Otherwise the card would have to be removed from the device each time the antenna is extended or retracted. This proposed modification to Hollander would render Hollander unsatisfactory for its intended purpose, and therefore there is no motivation to combine Hollander and Casarez.

The combination of Hollander and Casarez also does not teach or suggest an arrangement comprising locking means for setting a movable antenna structure in a position, as recited in claim 15. Hollander does not teach or suggest locking means comprising a pivoting position lever, as recited in claim 15 and acknowledged by the Examiner in paragraph 8 of the Office Action. Casarez does not teach or suggest placing an antenna structure inside a wireless communication device, and therefore does not suggest any locking means, such as a pivoting lever used with a lever guide, inside the wireless communication device for setting an antenna structure in different positions.


Since neither Hollander nor Casarez teach or suggest locking means comprising a pivoting position lever inside the wireless communication device, as recited in claim 15, their combination can not teach or suggest such a locking means. Therefore claim 15 is allowable. As claims 7-9 depend directly or indirectly from claim 1, claims 13 and 14 depend directly or indirectly from claim 11, and claim 16 depends from claim 15, claims 7-9, 13, 14, and 16 are also allowable.

For all of the foregoing reasons, it is respectfully submitted that all of the claims now present in the application are clearly novel and patentable over the prior art of record, and are in proper form for allowance. Accordingly, favorable

reconsideration and allowance is respectfully requested. Should any unresolved issues remain, the Examiner is invited to call Applicants' attorney at the telephone number indicated below.

The Commissioner is hereby authorized to charge payment for any fees associated with this communication or credit any over payment to Deposit Account No. 16-1350.

Respectfully submitted,


Michael Clorite
Registration No. 44,620

04/15/02
Date

Perman & Green, LLP
425 Post Road
Fairfield, CT 06430
(203) 259-1800
Customer No.: 2512


CERTIFICATE OF MAILING

I hereby certify that this correspondence is being deposited with the United States Postal Service on the date indicated below as first class mail in an envelope addressed to the Commissioner of Patents, Washington, D.C. 20231.

Date:

4/5/02

Signature:


Person Making Deposit

Application No.: 09/631,501

Marked Up Specification Replacement Paragraphs

Please delete the paragraph starting on page 1, line 4 through page 1, line 12 and replace with the following replacement paragraph:

The present invention relates to an expansion card [as set forth in the 5 preamble of claim 1]. The invention relates also to a method in the manufacture of an expansion card [as set forth in the preamble of claim 10]. Moreover, the invention relates to an antenna structure which is arranged to be fitted in a [card-like] wireless communication device card [, as set forth in the preamble of claim 11]. Furthermore, the invention relates to an arrangement for a wireless communication device for setting an antenna structure and guiding it in different positions [, as set forth in the preamble of claim 15].

Please delete the paragraphs starting on page 1, line 30 through page 2, line 33 and replace with the following replacement paragraphs:

According to prior art, various electronic devices, such as portable personal computers (PC) are often equipped with an expansion card interface, to which a standardized expansion card can be connected. These expansion cards are intended to form a functional unit with the PC. The expansion cards may also contain radio parts of a wireless communication device with its antenna, wherein the PC can, by means of this [card-like] wireless communication device card, communicate with other devices or with a communication network, e.g. the GSM network (Global System for Mobile Communication).

One known expansion card is the PC card complying with the PCMCIA standard (Personal Computer Memory Card International Association). The PCMCIA standard also defines the physical size of the PC card. The PC cards are fitted to be inserted fully inside the PC, but so-called extended PC cards can be longer than ordinary PC cards. These extended PC cards are placed partly outside the PC, wherein the thickness and design of the PC cards may vary in this part which typically also contains the antenna of the [card-like] wireless communication device card.

One known [card-like] wireless communication device card which comprises a transceiver with its antenna is the Nokia Cellular Card Phone, i.e. a card phone that can be connected to expansion card interfaces of types II and III of the PC card complying with the PCMCIA standard. One embodiment of the card phone of prior art is shown in Fig. 1, and the operation of the card phone is described in more detail e.g. in patent publication US 5,809,115. The card phone in question can comply with e.g. the GSM standard, wherein the PC device to which the card phone is connected can be in a wireless data transmission connection with base stations of a PLMN network (Public Land Mobile Network) by means of radio waves. In the card phone, the antenna part containing the antenna is placed in the part of the card phone located outside the PC device, and the antenna part is integrated with the [card-like] card part of the card phone which is placed inside the expansion card connection. Other known [card-like] wireless communication [devices] device cards are presented in patent publication US 5,628,055, wherein a separate turnable antenna can be connected to the end of the card, and in US 5,361,061, wherein a foldable antenna is pivoted at the end of the extended card on its upper surface. One [card-like] wireless communication device card is also disclosed in

the patent publication WO 97/49194, in which a card can be equipped with a separate fixed antenna part or, by means of a wire, a separate elongated antenna.

Please delete the paragraphs starting on page 3, line 8 through page 4, line 22 and replace with the following replacement paragraphs:

One drawback in known [card-like] communication [devices] device cards is the fact that during the use, particularly the antenna structure constitutes a part that protrudes from both the electronic device and the card. Moreover, the connections often comprise a protective cover to protect the expansion card, which must be kept open as the antenna structure extends outside the electronic device. The protruding parts of the antenna structure or of the card and protective covers may stick in something particularly during the transportation and use of the device, as well as they may damage the card or the antenna part. For this reason, the card must be detached after the use and be stored separately from the PC device for example during transportation; accordingly, a requirement for putting the device into working order is that the [card-like] wireless communication device card is inserted back in its place.

It is an aim of the present invention to eliminate the above-mentioned drawback and to present a considerable improvement to the prior art by means of a [card-like] wireless communication device card according to the invention. [The expansion card of the invention is characterized in what will be presented in the characterizing part of claim 1. The method in the manufacture of an expansion card according to the invention is characterized in what will be presented in the characterizing part of claim 10. An antenna structure according to the invention is characterized

in what will be presented in the characterizing part of claim 11. An arrangement according to the invention is characterized in what will be presented in the characterizing part of claim 15.]

A [card-like] wireless communication device card according to the invention, such as a card phone, has the considerable advantage that it can be made e.g. in the size of a PCMCIA card, wherein it fits fully inside e.g. the expansion card connection of a PC device. The [card-like] wireless communication device card preferably constitutes an integrated unit with standardized dimensions, and thanks to a push-in antenna, no protruding or separate parts will be formed in the structure of the card, wherein even an extended card will not comprise easily sticking or detachable elements.

The antenna structure of the invention can be placed, at least in its transportation position, fully inside the card, wherein the antenna structure is protected. Furthermore, it is an advantage of the [spring-like] spring operation that there is no need to provide the card or the antenna structure, particularly its end, with recesses, openings or extra parts for pulling the antenna out of the card, or to arrange closing devices or clamps for locking the antenna structure which would require space at the end of the card. Another advantage of the antenna structure is that its movement, thanks to the [spring-like] spring operation, can be arranged to be such that the antenna part is moved by its own force ready to its functional position at a correct distance from the device and from the card, wherein the user does not need to take care of pulling out the antenna part to this distance. Moreover, it is an advantage of the antenna structure that it can also be fitted in other wireless

communication devices of prior art, such as mobile phones. As an integrated structure, the antenna structure can also be easily installed and changed.

Please delete the paragraph on page 5, lines 6-13 and replace with the following replacement paragraph:

The [card-like] wireless communication device card according to the invention does not need to be removed from the PC device for the time of transportation. Thus, the start-up of the PC device, the setting up of the radio connection, and the start of wireless communication become faster. At the same time also the acts of inserting and removing the card in and from the expansion card connection are decreased, wherein the wear of the connection is reduced, and malfunctions are decreased.

Please delete the paragraphs starting on page 5, line 26 through page 12, line 31 and replace with the following replacement paragraphs:

In the following, the invention will be described in more detail with reference to the appended drawings, in which

Fig. 1 is a perspective view showing a [card-like] wireless communication device card according to prior art,

Fig. 2 is an explosion view showing a preferred embodiment of a [card-like] wireless communication device card according to the invention,

Fig. 3 is a perspective view showing a preferred embodiment of the [card-like] wireless communication device card of Fig. 2 partly cut open and the antenna part shown in its transportation position,

Fig. 4 is a perspective view showing a preferred embodiment of the [card-like] wireless communication device card of Fig. 2 partly cut open and the antenna part shown in an intermediate position,

Fig. 5 is a perspective view showing a preferred embodiment of the [card-like] wireless communication device card of Fig. 2 partly cut open and the antenna part shown in its functional position,

Fig. 6 is an explosion view showing a preferred embodiment of the [card-like] wireless communication device card of Fig. 2, and

Fig. 7 is a basic view showing the principle of operation of the antenna part according to Fig. 6 seen from above.

With reference to Figs. 2, [and] 6 and 7, a [card-like] wireless communication device card CP, which in the following will also be called a card CP, comprises a [card-like] card frame part [16-20] (comprising elements 16, 17, 18, 19 and 20) and an antenna structure [1-10] 25 (comprising elements 1, 2, 3, 4, 5, 6, 7, 8, 9 and 10) fitted inside the same at least in its transportation position, a position mechanism [11-13] (comprising elements 11, 12 and 13) for controlling the position of the antenna structure [1-10] 25 and fitting it movably in connection with the frame part [16-20], and coupling means [14-15] (comprising elements 14 and 15) for coupling the antenna structure [1-10] 25, particularly its antenna part 1 electrically to the circuit board 17 of the frame part [16-20] for the transmission of signals, such as radio signals. The [rod-like] antenna rod structure [1-10] 25 comprises a first end S1, in connection with which the antenna part 1 is placed for

receiving and transmitting signals in a wireless manner, and a second end S2 placed movably inside the card CP and equipped with coupling means 4 and locking means 5, 10, 12, 13 which shall be described further below. As shown in Fig. 2, the card CP comprises a first part, i.e. the frame part [16-20], and a second part, i.e. the antenna part [1-10] 25, which parts are arranged to move in relation to each other in the longitudinal direction of the card CP (axis X) e.g. by means of the position mechanism [11-13]. Thus, the moving can take place in this longitudinal direction X in a limited manner in both directions back and forth. The antenna structure can be moved into a first position A1 shown in Fig. 3, which in this description will be called the transportation position A1, a third position A3 shown in Fig. 4, which in this description will be called the intermediate position A3, and further to a second position A2 shown in Fig. 5, which in this description will be called the functional position A2. The radio parts of the card CP or the wireless communication device are located in the presented preferred embodiment of the invention in the frame part [16-20].

~~-----~~ Further with reference to Figs. 2 to 5, the card CP with the antenna structure [1-10] 25 is designed as a PC card complying with the PCMCIA standard. Thus, the card CP has an axis X with a longitudinal length of 85.6 mm and a transverse length of 54 mm according to the PCMCIA standard. However, an extended PC card can be 40 mm longer than this. PC cards are divided into three types, wherein the thickness of the card CP in its middle part can be 3.3 mm (type I), 5.0 mm (type II) or 10.5 mm (type III). PC cards are designed to be inserted fully inside the expansion card connection by a movement in the direction of the longitudinal axis X of the PC card (arrow X2). The PC card is typically equipped with a 68-pin connector complying with the

PCMCIA standard, by means of which the PC card is coupled to an electronic device, such as a PC. At the location of this connector and at the edge of the PC card the thickness of the PC card is 3.3 mm.

With reference to Fig. 2, the card CP normally comprises connector means 20 and frame means 18 which can be made of plastic, wherein the circuit board 17 of the card CP and the radio parts placed on the circuit board, such as a transceiver (not shown in the figures) are located inside the card CP. The cover structures 16 and 19 are usually planar and substantially equiform thin sheet structures, such as structures made of e.g. metal. As shown in Fig. 2, the card CP comprises a separate cover structure 16, but the cover structure 19 and the frame structure 18 constitute an integrated unit, where the unit can be made e.g. by casting. It is obvious that the frame structure 18 with its reinforcements can also be made separately and e.g. fixed to the cover structure 19.

The connector means 20 are fixed to a circuit board 17 placed inside the card CP. The circuit board 17 also comprises the components necessary for the functions of the card CP, ~~such as~~ integrated circuits (IC, not shown in the figures) and wirings (not shown in the figures) for the transmission of electric signals, such as radio signals, between the connector means 20 and the components. At the same time the circuit board 17, the components and wirings arranged on the circuit board 17, as well as the coupling means [14-15] form the means for processing the signals, such as radio signals. Further, with reference to [Figs. 3 and 5] Fig. 2, the coupling means [14-15] are needed for transferring the signals between the antenna structure [1-10] 25 of the card CP and the components of the circuit board

17. The electronic operating principle of the [card-like] wireless communication device card, such as a card phone as mentioned above, is known as such to anyone skilled in the art, wherein a more detailed description will not be necessary in this context.

Further with reference to Fig. 2, when the antenna structure [1-10] 25 is fitted in the card CP and particularly in the desired positions of the antenna structure, such as in the positions A1 and A2, one must also take care of the coupling of the antenna signal and, if necessary, also of the coupling of the ground potential to the antenna part 1. The elongated [and rod-like] antenna rod structure is also placed in alignment with the axis X and the direction of pushing (arrow X1 in Fig. 4), wherein the antenna structure is advantageously shorter than the card CP in order to fit inside the card CP. By using the connector means 20, the card CP is, for the transmission of signals, coupled to the expansion card connection of the PC device, which is equipped with pins which protrude in openings formed in the connector means 20 and having contacts whereby the pins are electrically coupled to the wirings and components of the circuit board 17. With respect to the connector means 20, the antenna structure is located on the next side of the card CP and arranged to extend from the opposite end outside the card CP, wherein when the card CP is fully inside the expansion card connection, the antenna structure can be moved by a pushing movement (arrow X1 in Fig. 4) out of the card CP and simultaneously out of the connection and farther from the electronic device. The antenna structure moves in the direction of the planes of the cover structures and protrudes from the card CP from between the cover structures and from a circumferential outer surface edging the card CP.

The card CP comprises a position mechanism [11-13] operating in a [spring-like] spring manner for moving the antenna structure by pushing into the positions A1, A2 and A3 mentioned above. The position mechanism [11-13] is arranged to release the antenna structure from the transportation position A1 to the intermediate position A3 and further to move and set it to the functional position A2, as well as to move the antenna structure from the functional position A2 to the intermediate position A3 and further back to the transportation position A1, to be locked. The pushing, which can be performed with e.g. with a finger, is performed in the direction compressing the pressure spring 11 of said mechanism (arrow X1 in Fig. 4). The transportation position A1 is substantially located between the functional position A2 and the intermediate position A3.

Figure 6 shows a preferred embodiment of the antenna structure [1-10] 25 comprising a [rod-like,] rigid antenna rod housing 2, which [is] can be made of e.g. plastic, and which is open at its one end, inside which the elongated, [strip-like] strip antenna part 1 is located to be shielded. The planar antenna part 1 can ~~itself constitute the required antenna, or the surface of the~~ [strip-like] strip antenna part 1 can be provided with a separate antenna element e.g. by means of a microstrip. The antenna part 1 is attached to a stake 3 which at its end on the side of the antenna part 1 is partly fitted inside the antenna housing 2, in an opening 2a, and at its opposite end is fitted inside a sleeve 6, in an opening 6a. The sleeve 6 constitutes an elongated housing structure which is preferably open at its one end. The antenna housing 2 and the sleeve 6 are fitted to adjoin each other, wherein their openings 2a and 6a face each other and the stake 3 fitted in said openings is fully placed inside them. The stake 3 can be fixed to the antenna housing 2 in various

ways. The stake 3 is provided with a transverse opening 3a extending through the stake 3 and accommodating a transverse contact pin 4. The purpose of the contact pin 4 is to couple the antenna part 1 electrically to the circuit board 17 of Fig. 2. The sleeve 6 is provided with an opening 6b which extends in the transverse direction through its wall to the hollow inner part and which is arranged to receive the contact pin 4. Around the opening 6b, the sleeve 6 is provided with a [collar-like] collar part 6c supporting the contact pin 4. Fitted in the opening 6b, the contact pin 4 extends through the inner part of the sleeve 6 to the opposite wall which has a receptacle 6d supporting the end of the contact pin 4. Of the receptacle 6d, only a protruding part extending outside the sleeve 6 is visible, which is also equipped with a protruding spring stopper 7 for the pressure spring 11 of Fig. 2 and for pushing the antenna structure [1-10] 25 out of the card CP. Inside the sleeve 6 is arranged a pressure spring 5 which is fitted by compressing under the stake 3 and which pushes the stake 3 out of the sleeve 6. The stake 3 remains, however, inside the sleeve 6 when the contact pin 4 is fitted both in the opening 6b and in the opening 3a.

The closed, outermost end of the sleeve 6 is provided with a [nest-like] nest recess or opening 8 equipped with a planar surface 9 which is perpendicular to the longitudinal direction Y of the antenna structure [1-10] 25 (which is parallel to the longitudinal direction X of the card CP). The planar surface 9 is fitted in the sleeve 6 in such a way that a position lever 10 can be supported against the planar surface 9, wherein the pressure spring 5 presses the position lever 10 placed between the spring 5 and the surface 9 against the planar surface 9. The pressure spring 5 is supported at its one end to the stake 3.

The nest 8 also accommodates a transverse part which extends from the position lever 10 extending in the direction of the axis Y and which is equipped with a planar surface 10a. The nest 8 is arranged in such a way that it allows the pivoting of the position lever 10 in a side direction in a plane that is substantially parallel with the cover structure 16 of Fig. 2. A hole 6e extends from the nest 8 into the sleeve 6 to accommodate the spring 5. When the position lever 10 is turned, its planar surface 10 and the planar surface 9 are placed in an angle, but the pressure spring 5 tends to press the position lever 10 against the planar surface 9, which causes straightening of the position lever 10 and setting of the planar surfaces 9 and 10a in parallel to and against each other.

With reference to Figs. 2 and 6, the side of the sleeve 6 is also equipped with a spring stopper 7 for the purpose of compressing the spring means fitted in the frame structure 18, such as a pressure spring 11, which is preferably a helical spring. For the pressure spring 11, the frame structure 18 is equipped with an elongated spring nest 18a in the direction of the antenna structure [1-10] 25 (axis Y), to which the spring stopper 7 extends and in which the spring stopper 7 is movable. When the antenna structure is inserted in the card CP, also the pressure spring 11 is compressed and tends to push the antenna structure out of the card CP, wherein it generates a counter force for the insertion. The nest 18a is also equipped with an end stopper 18b which is hit by the spring stopper 7 and which prevents that the antenna structure is completely detached from the card CP. The frame structure 18 is also provided with an antenna nest 18c for the antenna structure [1-10] 25, in which the antenna structure is allowed to move in the direction of the axis Y. The nest 18c is opened to the end of the card CP, from

which the antenna structure is pushed out and thereby extends outside the card CP.

The function of the pressure spring 11 is to produce a force which is opposite to the direction of pressing (arrow X1 in Fig. 4), to move the antenna structure [1-10] 25. Consequently, to move the antenna structure to different positions, preferably only a finger movement is required in the direction of pressing (arrow X1 in Fig. 4) and a pressing force for compressing the pressure spring 11, after which, when the finger is released, the antenna structure automatically springs out in the opposite direction.

As shown in Fig. 6, the outermost end of the position lever 10 is provided with a pin 10b for the purpose of moving along a path P shown in Fig. 7, under the guidance of lever guides 12 and 13 shown in Fig. 2 and formed in the frame structure 18 or alternatively fixed in the cover structure 19. Along the path P, the antenna structure is set in the different positions A1, A2 and A3. In the presented embodiment, the pin 10b, when straightened, is set parallel to the axis Y. It should be noted that the terms describing the different positions A1, A2, A3 (intermediate position, functional position, transportation position) are only given for illustrating the function and various positions of the antenna structure [1-10] 25 and to separate the different positions from each other, and they do not describe the precise position of the antenna structure [1] 25. However, for example the transportation position A1 is preferably the position in which the antenna structure is locked and placed fully inside the card CP. The location of the functional position A1 can vary even to a great extent, for example, depending on [e.g.] the location of the end stopper

18b, but in this position the antenna structure, particularly the antenna part 1 is located as far as possible from the frame parts [16-20] of the card CP.

The antenna part 1 is electrically coupled to the circuit board 17 of the 5 card CP by means of the contact pin 4. The antenna part 1 is coupled to the contact pin 4 for example by means of wires or [spring-like] spring contact means (not shown in the figure), and the contact pin 4 can be made of an electroconductive material e.g. metal, or it can be coated with an electroconductive material. The ground potential possibly required by the antenna part 1 can be coupled in a variety of ways, e.g. through the stake 3 and the sleeve 7 and/or the antenna housing 2, wherein they must be equipped with electroconductive surfaces or contacts. In the functional position A2 of the antenna structure, the contact pin 4 is arranged in contact with the circuit board 17 with a contact spring 14 fitted according to Fig. 2, by means of which the antenna part 1 is electrically coupled to the wirings and components of the circuit board 17. When inserted, the connection between the contact pin 4 and the contact spring 14 is cut off. If necessary, the circuit board 17 can also be equipped with another contact spring 15, as shown in Fig. 2, in the location in which the contact pin 4 is set in the transportation position A1 of the antenna structure, wherein the antenna part 1 and the circuit board 17 have an electric contact to each other. It is obvious that the stake 3 can be equipped with several contact pins which are each electrically coupled to the circuit board by means of a contact spring. The contact springs and the way of their attachment can be different from that presented, and they can be, for example, elongated, [slide-like] slide means along which the contact pin 4 slides in the contact. It is also

possible that the operation of the radio parts of the card CP is coupled on and off depending on the position of the antenna structure 1, or on the contact spring to which the antenna part 1 is coupled. For example, the operation is turned off in the first position A1 and turned on in the second position A2.

Please delete the paragraphs starting on page 13, line 5 through page 14, line 21 and replace with the following replacement paragraphs:

The lever guide 12 comprises a triangular structure to be fitted on the longitudinal axis Y and in a functional connection with the pin 10b of the position lever 10, one tip of the triangle diagonally pointing at the antenna structure. The sides next to the tip are preferably planar, and the side opposite to the tip is formed as a concave surface. Close to said concave surface is also arranged the second lever guide 13 which guides the pin 10b to follow said concave surface with a curvilinear movement and which prevents the lever 10 from being straightened to be parallel with the antenna part 1 in the intermediate position. The pressure spring 5, the position lever 10, and the lever guides 12 and 13, which are all arranged in a functional connection with each other, constitute the locking means which form an arrangement for setting and guiding the antenna structures in the different positions, particularly by a movement of a [spring-like] spring means, such as the pressure spring 11. The arrangement can be utilized in connection with various antenna structures, wherein for example by extending the stake 3, the antenna part 1 with the antenna housing 2 can be placed fully outside the wireless communication device. The antenna part 1 can also be fixed to the stake 3 also in the perpendicular direction, wherein the attachment of the antenna

part 1 and the antenna housing 2 to the stake 3 can be arranged in such a way that pivoting around the longitudinal direction into the different positions is possible. Naturally, it is obvious that in said arrangement, the attachment of the stake 3 and the sleeve 6 as well as the antenna part to the arrangement can be different from that presented. It is also obvious that the assembly of the antenna structure itself can also vary from that presented and may comprise e.g. means for processing signals and several connecting means.

With reference to [Fig.] Figs. 6 and 7, we shall now look into the operation of the position mechanism [11-13]. Figure 7 shows a path P which is particularly followed by the pin 10b of the lever 10. The antenna structure [1-10] 25 moves back and forth in its longitudinal direction in the card CP (arrow Y), and also the pin 10b is primarily in the straightened position, pushed by the pressure spring 5 of Fig. 5. When the antenna structure is inserted in the card CP, the pin 10b is set in a functional connection with the lever guides 12 and 13 which guide the position lever 10 by deflecting it from the rest position maintained by the spring 5 into different positions. By means of said positions, also the antenna structure is set in the positions A1, A2 and A3 mentioned above. When the antenna structure is inserted from the functional position A2 of Figs. 5 and 7, the lever guide 12 guides the pin 10b to the side (groove Pa), until the pin 10b passes the edge of the guide and tends to be straightened, i.e. to be returned to its rest position, by means of the spring force. However, the straightening is prevented by the lever guide 13 which is hit by the pin 10b which remains in a slanted position (location Pb). Thus, the antenna structure is set in its intermediate position A3, shown in Fig. 4, which is not permanent but the antenna structure is

moved from its intermediate position A3 to the transportation position A1. The antenna structure does not remain locked in its intermediate position A3 which is only used as an intermediate phase required for moving the position mechanism into different positions. The pin 10b is arranged to move past the lever guide 13 in the perpendicular direction only between the lever guides 12 and 13, for example by preventing insertion of the antenna structure too far in the card CP, or by the design of the lever guide 13.

Please delete the paragraph on page 15, lines 7-25 and replace with the following replacement paragraph:

According to a second embodiment of the invention, the antenna structure [1-10] 25 and the position mechanism [11-13] are arranged in such a way that the pressure spring 5, the nest 8 and the planar surface 9 are fitted to a location in which the parts 12 and 13 are found in Fig. 2. In a corresponding manner, the lever guides 12 and 13 are thus fitted in the sleeve 6 and the position lever 10 is fitted in the nest 8. Thus, the position of said parts is also turned 180 degrees around the direction perpendicular to the direction Y. Furthermore, it is obvious that in comparison with the second embodiment and the first embodiment of Fig. 2, the position of said parts can also be turned around the direction Y, for example 90 or 180 degrees, wherein the lever guides 12, 13 can also be attached to the cover structure 16. The lever guides 12, 13 can also be arranged to be fixed to the circuit board 17. In Fig. 2, the antenna structure is placed to the right-hand side of the card CP, but its position can also be on the left-hand side of the card, where also another corresponding antenna structure can be placed. It is obvious that the antenna structure can also be

placed in the middle part of the card CP; however, this will make the internal structure of the card CP more complicated.

Marked Up Specification Replacement Section(S)

Please delete the title (page 1, line 1), and replace with the following title:

A [card-like] wireless communication device card and an antenna structure

"Abstract" (page 21, lines 3-24):

[The present invention relates to an] An expansion card, preferably a wireless communication device, which card [(CP)] is arranged to be fitted in the expansion card connection of an electronic device and which comprises a frame part [(16-20)]. In the invention, the card [(CP)] is provided with [a rod-like] an antenna rod structure [(1-10)] comprising a first end [(S1)] equipped with an antenna part [(1)] and a second end [(S2)] to be fitted movably inside said frame part [(16-20)], wherein said antenna part [(1-10)] is arranged to be movable for inserting the antenna part [(1-10)] in said card [(CP)] and for extending the first end [(S1)] outside said card [(CP)]. The arrangement of the invention for setting and guiding the antenna structure [(1-10)] to different positions [(A1, A2)] comprises locking means [(5, 10, 12, 13)] which comprise a position lever [(5, 10)] arranged to be deflected to the side direction and to return and arranged in a functional connection with designed lever guides [(12, 13)], which lever guides [(12, 13)] are arranged upon inserting said antenna structure [(1-10)] to deflect said position lever [(5, 10)] to a position which prevents the pushing out of said antenna structure [(1-10)], and is arranged upon pushing said antenna structure [(1-10)] further

inwards to allow the return of said position lever [(5, 10)] to a position which allows the pushing out of said antenna structure [(1-10)].

[(Fig. 2)]

Marked Up Claim(s)

1. (Amended) An expansion card, [which] wherein the card [(CP)] is arranged to be fitted in an expansion card connection of an electronic device, such as a data processor, and which card comprises a frame part [(16-20)], [characterized in that] wherein the card [(CP)] is provided with an antenna structure [(1-10)] which is [formed as] a [rod-like] rod structure comprising a first end [(S1)] with an antenna part [(1)] for receiving and transmitting signals, and a second end [(S2)] placed movably inside said frame part [(16-20)], wherein said antenna structure [(1-10)] is arranged to be movable for inserting the antenna structure [(1-10)] in said card [(CP)] and for extending the first end [(S1)] outside said card [(CP)].

2. (Amended) The expansion card according to claim 1, [characterized in that] wherein it is a [card-like] wireless communication device card [(CP)], wherein said frame part [(16-20)] is provided with means [(14, 15, 17)] for processing signals, and that the second end [(S2)] of said antenna structure [(1-10)] is provided with connecting means [(4)] for transferring signals between said antenna structure [(1-10)] and said means [(14, 15, 17)] for processing signals.

3. (Twice Amended) The expansion card according to claim 1, [characterized in that] wherein it is formed at least partly as a card [(CP)] complying with a standard, such as the PCMCIA

standard, being preferably 85.6 mm long, preferably 54 mm wide and preferably not more than 3.3 mm, 5.0 mm or 10.5 mm thick.

4. (Twice Amended) The expansion card according to claim 1, [whose] wherein the frame part [(16-20)] comprises connector means [(20)] for connecting said card [(CP)] electrically to said expansion card connection, [characterized in that] wherein the antenna structure [(1-10)] is arranged to be pushed out at the opposite end of said card [(CP)] with respect to said connector means [(20)].

5. (Twice Amended) The expansion card according to claim 1, [characterized in that] wherein said antenna structure [(1-10)] is arranged to be pushed out by a spring means [(11)] fitted inside said card [(CP)].

6. (Twice Amended) The expansion card according to claim 1, [characterized in that] wherein said antenna structure [(1-10)] is arranged to be locked at its first position, by first inserting it by pushing it inwards, further than its first position, wherein locking is activated, and then releasing it, and allowing it to move back to its first position [(A1)], in which said antenna structure [(1-10)] is, preferably entirely, inside said card [(CP)], and that said antenna structure [(1-10)] is arranged to move from the first position [(A1)] to its second position [(A2)] by first pushing said antenna structure [(1-10) more] inwards, further than its first position, and then releasing it, wherein locking is de-activated, and allowing it to move back past its first position and stop at its second

position, wherein in the second position [(A2)] said antenna structure [(1-10)] extends, preferably as far as possible, outside said card [(CP)].

7. (Amended) The expansion card according to claim 6, [characterized in that] wherein said antenna structure [(1-10)] is arranged to be locked in its position by means of locking means [(5, 10, 12,13)] fitted in connection with the second end [(S2)], which locking means [(5,10,12,13)] comprise a pivoting position lever [(5, 10)] arranged to be deflected sideways and back again [to the side direction and to return] and arranged to be guided by [in a functional connection with designed] lever guides [(12,13)], which lever guides [(12,13)] are arranged upon inserting said antenna structure [(1-10)] to deflect said position lever [(5, 10)] to a position which prevents the pushing out of said antenna structure [(1-10)] and thereby activating locking, and are arranged upon pushing said antenna structure [(1-10)] further inwards to allow the return of said position lever [(5, 10)] to a position which allows the pushing out of said antenna structure [(1-10)] and thereby activating locking.

8. (Amended) The expansion card according to claim 7, [characterized in that] wherein said lever guides [(12,13)] comprise at least a first[, preferably triangular] part [(12)] which comprises side surfaces arranged to be followed by a pin [(10b)] fitted in said position lever [(5, 10)] and behind which said pin [(10b)] is arranged to be set when being deflected at the same time, and [preferably] also a second part [(13)] which is arranged to keep said pin [(10b)], which has passed the first

part [(12)], deflected and to guide it behind the first part [(12)] for activating locking.

9. (Twice Amended) The expansion card according to claim 7, [characterized in that] wherein said position lever [(10)] is arranged at the second end of said antenna structure [(1-10)], and that said lever guides [(12, 13)] are fitted in a fixed manner inside said frame part [(16-20)].

10. (Amended) A method in the manufacture of an expansion card, [which] wherein the card [(CP)] is arranged to be fitted in the expansion card connection of an electronic device, such as a data processor [processors], and which card comprises a frame part [(16-20)], [characterized in that] wherein the card [(CP)] is provided with an antenna structure [(1-10)] which is [formed as] a [rod-like] rod structure comprising a first end [(S1)] provided with an antenna part [(1)] for receiving and transmitting signals, and a second end [(S2)] placed movably ~~inside said frame part [(16-20)],~~ wherein said antenna structure [(1-10)] is arranged to be movable for inserting the antenna structure [(1-10)] in said card [(CP)] and for extending the first end [(S1)] outside said card [(CP)].

11. (Amended) An antenna structure which is arranged to be fitted in a wireless communication device [(CP), such as a mobile phone and an expansion card], [which] wherein the device comprises a frame part [(16-20)] provided with means [(14, 15, 17)] for processing signals, [characterized in that] wherein said antenna structure [(1-10)] is [formed as] a [rod-like] rod

structure comprising a first end [(S1)] provided with an antenna part [(1)] for receiving and transmitting signals, and a second end [(S2)] which is to be placed movably inside said frame part [(16-20)] and which is provided with connecting means [(4)] for transferring signals between said antenna structure [(1-10)] and said means [(14, 15, 17)], wherein said antenna structure [(1-10)] is arranged to be movable for inserting the antenna structure [(1-10)] in said wireless communication device [(CP)] and extending the first end [(S1)] outside said wireless communication device [(CP)].

12. (Amended) The antenna structure according to claim 11, [characterized in that] wherein it is arranged to be pushed out by a spring means [(11)] fitted inside said frame part [(16-20)].

13. (Twice Amended) The antenna structure according to claim 11, [characterized in that] wherein it is arranged to be locked in its position with locking means [(5,10,12,13)] fitted in connection with the second end [(S2)], which locking means [(5, 10, 12, 13)] comprise a pivoting position lever [(5, 10)] arranged to be deflected sideways and back again [to the side direction and to return] and arranged to be guided by [in a functional connection with designed] lever guides [(12, 13)], which lever guides [(12, 13)] are arranged upon inserting said antenna structure [(1-10)] to deflect said position lever [(5, 10)] to a position which prevents the pushing out of said antenna structure [(1-10)] and thereby activating locking, and are arranged upon pushing said antenna structure [(1-10)] further inwards to allow the return of said position lever [(5,

10)] to a position which allows the pushing out of said antenna structure [(1-10)] and thereby activating locking.

14. (Amended) The antenna structure according to claim 13, [characterized in that] wherein said position lever [(10)] is arranged at the second end [(S2)] of said antenna structure [(1-10)] and that said lever guides [(12, 13)] are arranged in a stationary manner inside said frame part [(16-20)].

15. (Amended) An arrangement for a wireless communication device [(CP)], [such as a mobile phone or an expansion card,] for setting and guiding an antenna structure [(1-10)] in different positions [(A1, A2)], [characterized in that]

wherein said antenna structure [(1-10)] comprises a first end [(S1)] which is provided with an antenna part [(1)] for receiving and transmitting signals, and a second end [(S2)] to be fitted movably inside said wireless communication device [(CP)],

wherein the arrangement comprises a spring means [(11)] to be fitted inside said wireless communication device [(CP)], for pushing out said antenna structure [(1-10)],

wherein the arrangement comprises locking means [(5, 10, 12, 13)] for setting said antenna structure [(1-10)] in its first position [(A1)], which locking means [(5, 10, 12, 13)] comprise a pivoting position lever [(5, 10)] arranged to be deflected sideways and back again [to the side direction and to return] and arranged to be guided by [in a

functional connection with designed] lever guides [(12, 13)], which lever guides [(12,13)] are arranged upon inserting said antenna structure [(1-10)] by pushing it inwards to deflect said position lever [(5, 10)] to a position which prevents the pushing out of said antenna structure [(1-10)], wherein locking is activated, and which lever guides are arranged upon pushing said antenna structure [(1-10) further] inwards, further than its first position, wherein locking is activated, to allow the return of said position lever [(5, 10)] to a position which allows the pushing out of said antenna structure [(1-10)] to its second position [(A2)], and

wherein the first position [(A1)] is arranged for bringing the antenna part [(1)] to the inside of or closer to said wireless communication device [(CP)] and the second position [(A2)] is arranged for bringing the antenna part [(1)] out of or farther from said wireless communication device [(CP)].

16. (Amended) The arrangement according to claim 15, [characterized in that] wherein said position lever [(10)] is fitted at the second end [(S2)] of said antenna structure [(1-10)] and that said lever guides [(12, 13)] are integrated in said wireless communication device [(CP)].